



- For indoor use only.
- Product installation must be carried out by a qualified professional.
- Before installing make sure, that electrical power is turned **OFF**.
- Before installing make sure, that the fixing area can bear the total weight of the luminaire.
- Pay attention to polarity when connecting (installing) the product.
- Do not operate if the luminaire has been damaged.
- To protect the surface from dirt and fingerprints, we recommend the use of protective gloves during installation.
- Product warranty does not cover any damage caused by faulty installation and/or misuse.
- For further information, please contact the manufacturer.

Luminaire	Cutting hole size by Segment type, mm (ft)				Luminaire	Cutting hole size by Segment type, mm (ft)			
	Start	Middle	End	Width		Start	Middle	End	Width
L-560	564 (1.85)	560 (1.84)	564 (1.85)	38 mm (1.49")	L-1960	1964 (6.44)	1960 (6.43)	1964 (6.44)	38 mm (1.49")
L-840	844 (2.77)	840 (2.76)	844 (2.77)		L-2240	2244 (7.36)	2240 (7.35)	2244 (7.36)	
L-1120	1124 (3.69)	1120 (3.67)	1124 (3.69)		L-2520	2524 (8.28)	2520 (8.27)	2524 (8.28)	
L-1400	1404 (4.61)	1400 (4.59)	1404 (4.61)		L-2800	2804 (9.2)	2800 (9.19)	2804 (9.2)	
L-1680	1684 (5.52)	1680 (5.51)	1684 (5.52)		L-3080	3084 (10.12)	3080 (10.1)	3084 (10.12)	
Example: 564+560+564=1688 mm				Cutting hole size: 1688 mm x 38 mm (5.54' x 1.49")					

Min ceiling thickness 10 mm (0.39 in) Max ceiling thickness 40 mm (1.57 in)



